

Table of Contents

- Supported Cameras, Encoders, I/O Modules
- Supported Accessories
- Supported VoIP Devices

Important to know

General

- This document indicates which features of each device are implemented in SeeTec 5.
- This document does not show which features each device has.
- Of course this implementation depends on the available features of each device.
- **Bold red** devices/features are new since the previous public release.

Video Motion detection (VMD) and Analytics

Method 1) Notification via polling or via separate stream like e.g. Server Push

Method 2) Notification InStream: Image stream contains motion detection information. Requires activated standard recording!

Method 3) Notification via TCP Trigger. TCP trigger has to be configured manually on the camera. Requires "SeeTec Network IO"

*No of Streams (Multistreaming)

- That does not mean multiple camera sources
- It means simultaneous streams from one source with different settings (Codec, resolution, framerate, etc.)
- It is important to check the total number of streams. This is the decisive value.
Example: MJPEG: 1; MPEG-4: 1; H.264: 2; Overall: 2 means that there are only 2 simultaneous streams available.
- Multiple streams can reduce the performance (framerate, resolution etc.) of each stream (depending on the camera)
- Simultaneous streaming of MPEG-4 and H.264 is not possible at all

****Each digital I/O connector is configurable (on camera side) whether it is used as input or output.**

*****Audio of IP-cameras and encoders are supported only for MPEG-4/H.264 and only one way (listen/record).**

For multi channel encoders with only one IP address audio can only be used for channel 1

******VoIP devices use SIP protocol. VoIP-connection for calls only. No continuous recording! SIP server required.**

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
ACTi TCM-56xx	3.08.08 (5.2.8)	5.2.8	1	1	-	-	1	-	2/2	x	x	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi ACD-2200	2.03.06 (5.2.8) 3.08.08 3.12.15	5.2.8	1	1	-	-	1	-	2/-	x	x	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi ACM-1011		5.3.4	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-11xx		5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-12xx/15xx	3.08.08 (5.2.8) 3.09.14	5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-13xx/14xx		5.2.8	1	1	-	-	1	-	-	-	x	² X	-	-	-	-	-	
ACTi ACM-30xx	3.11.13 (5.3.4)	5.3.4	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-31xx		5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-32xx/33xx	3.08.08 (5.2.8)	5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-34xx	3.08.08 (5.2.9)	5.2.9	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-35xx	3.08.08 (5.2.9)	5.2.9	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-36xx	3.11.13 (5.3.4)	5.3.4	1	1	-	-	1	-	-/-	-	-	² X	-	-	-	-	-	
ACTi ACM-37xx	3.08.08 (5.2.8) 3.09.14	5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-40xx/41xx	3.08.08 (5.2.8) 3.09.14	5.2.8	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-42xx		5.3.4	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-5001	3.08.08 (5.2.8)	5.2.8	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-56xx	3.08.08 (5.2.8)	5.2.8	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-57xx		5.2.8	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-58xx		5.3.4	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-74xx	3.08.08 (5.2.10)	5.2.10	1	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi ACM-82xx	3.11.13 (5.2.6)	5.3.6	1	1	-	-	1	-	1/1	x	x	² X	-	-	-	-	-	
ACTi ACM-85xx	3.11.13 (5.2.6)	5.3.6	1	1	-	-	1	-	1/1	x	x	² X	-	-	-	-	-	
ACTi CAM-52xx		5.2.8	-	1	-	-	1	-	-/-	-	x	² X	-	-	-	-	-	
ACTi CAM-53xx	2.08.11 (5.2.8)	5.2.8	-	1	-	-	1	-	-/-	-	-	² X	-	-	-	-	-	
ACTi CAM-65xx/66xx		5.2.8	-	1	-	-	1	-	8/1	x	x	² X	-	-	-	-	-	
ACTi CAM-72xx		5.2.8	-	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi CAM-73xx	2.08.11 (5.2.8)	5.2.8	-	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi ACM-75xx		5.3.4	1	1	-	-	1	-	1/1	-	x	² X	-	-	-	-	-	
ACTi SED-2120 Series		5.2.8	-	1	-	-	1	-	2/2	x	-	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi SED-2140 Series		5.2.8	-	1	-	-	1	-	2/2	x	x	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi SED-2320Q		5.2.8	-	1	-	-	1	-	1/1	x	x	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi SED-2610		5.2.8	-	1	-	-	1	-	16/16	x	x	² X	-	-	-	-	-	PTZ: only Pelco D protocol
ACTi TCD-2100	4.08.05 (5.3.7)	5.3.7	2	-	2	-	2	-	1/1	x	-	² X	-	-	-	-	-	PTZ: only Pelco D protocol Multistreaming requires SeeTec Version 5.4.0 or higher



SeeTec 5 Supported Cameras, Encoders, I/O Modules

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
ACTi TCD-2500	4.08.05 (5.3.7)	5.3.7	2	-	2	-	2	-	2/1	x	x	2)X	-	-	-	-	-	PTZ: only Pelco D protocol Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-12xx/15xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-30xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-34xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-35xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-4301	4.02.04 (5.3.2) 4.09.22 (5.4.0)	5.3.2	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-53xx	4.04.06 (5.3.2) 4.09.22 (5.4.0)	5.3.2	2	2	2	-	2	-	1/1	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-56xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	1/1	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
ACTi TCM-74xx	4.07.15 (5.3.5) 4.09.22 (5.4.0)	5.3.5	2	2	2	-	2	-	-/-	-	x	2)X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.4.0 or higher
AcutVista 6000-A	5.a.1.3712 (5.3.7)	5.3.7	1	-	1	-	1	-	1/1	x	x	1)X	-	-	-	-	-	
Advantech ADAM 6050 (W)		5.2.8	-	-	-	-	-	-	12/6	-	-	-	-	-	-	-	-	
Advantech ADAM 6052	1.19 (5.2.8)	5.2.8	-	-	-	-	-	-	8/8	-	-	-	-	-	-	-	-	
Advantech ADAM 6060 (W)	2.02 (5.2.8) 4.09	5.2.8	-	-	-	-	-	-	6/6	-	-	-	-	-	-	-	-	
Advantech ADAM 6066	2.02 (5.2.8) 4.09	5.2.8	-	-	-	-	-	-	6/6	-	-	-	-	-	-	-	-	
Arecont Vision AV1300 (DN)		5.2.8	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV2100 (DN)	63115 (5.2.8)	5.2.8	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV3100 (DN)	63418 (5.2.8)	5.2.8	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV3130	64329 (5.2.8)	5.2.8	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV5100 (DN)	62603 (5.2.8)	5.2.8	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV1310 (DN)	65142 (5.3.3)	5.3.3	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV2110 (DN)	65142 (5.3.3)	5.3.3	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV3110 (DN)	65142 (5.3.3)	5.3.3	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV5110 (DN)	65142 (5.3.3)	5.3.3	8	-	-	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV1305 (DN)	64828 (5.2.9)	5.2.9	8	-	8	-	8	x	1/1	-	-	1)X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher



SeeTec 5 Supported Cameras, Encoders, I/O Modules

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Arecont Vision AV1315 (DN)	65191 (5.3.8)	5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV1325 (DN)	65192 (5.3.8)	5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV2105 (DN)		5.2.9	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV2805 (DN)	65192 (5.3.8)	5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV2815 (DN)		5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV2825 (DN)	65192 (5.3.8)	5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV3105 (DN)	64828 (5.2.9) 65139	5.2.9	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV5105 (DN)	64828 (5.2.9)	5.2.9	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV1355 (DN)		5.2.13	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV2155 (DN)	64829 (5.2.13)	5.2.13	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV3155 (DN)		5.2.13	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV5155 (DN)		5.2.13	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7 VCam support requires SeeTec version 5.3.7 or higher
Arecont Vision AV10005 (DN)	65147 (5.3.8)	5.3.8	8	-	8	-	8	x	1/1	-	-	¹⁾ X	-	-	-	-	-	
Arecont Vision AV8180	62410 (5.2.8) 64414	5.2.8	1	-	-	-	1	-	-/-	-	-	-	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7
Arecont Vision AV8360		5.2.8	1	-	-	-	1	-	-/-	-	-	-	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7
Arecont Vision AV8185 (DN)	65026 (5.3.4)	5.3.4	1	-	1	-	1	-	-/-	-	-	-	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7
Arecont Vision AV8365 (DN)	65026 (5.3.4)	5.3.4	1	-	1	-	1	-	-/-	-	-	-	-	-	-	-	-	Lower resolutions are only cropped before SeeTec Version 5.3.7
Axis 200+		5.2.8	3	-	-	-	3	-	-/-	-	-	-	-	-	-	-	-	
Axis 205		5.2.8	3	-	-	-	3	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Axis 206	4.40 (5.2.8)	5.2.8	3	-	-	-	3	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Axis 206M	4.40 (5.2.8)	5.2.8	3	-	-	-	3	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Axis 206W	4.40 (5.2.8)	5.2.8	3	-	-	-	3	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Axis 207	4.40.1 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	-	¹⁾ X	-	-	-	x	x	
Axis 207MW	4.40.1 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 207W	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 209FD (-R)		5.2.8	3	1	-	-	4	-	-/-	-	-	¹⁾ X	-	-	-	x	x	
Axis 209MFD (-R)		5.2.8	3	1	-	-	4	-	-/-	-	-	¹⁾ X	-	-	-	x	x	
Axis 210	4.20 (5.2.8) 4.30 (5.2.8) 4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	-	¹⁾ X	-	-	-	x	x	
Axis 210A	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 211	4.20 (5.2.8) 4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	-	¹⁾ X	-	-	-	x	x	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Axis 211A	4.30 (5.2.8) 4.40 (5.2.8) 4.40 1 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 211M	4.41 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 211W	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 212	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	x	x	¹⁾ X	-	-	-	x	x	
Axis 213	4.30 (5.2.8)	5.2.8	3	1	-	-	4	-	2/3	x	x	¹⁾ X	-	-	-	-	x	
Axis 214	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	x	x	¹⁾ X	-	-	-	x	x	
Axis 215		5.2.8	3	1	-	-	4	-	1/1	x	x	¹⁾ X	-	-	-	-	x	
Axis 216FD (-V)	4.40 (5.2.8) 4.47 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 216MFD (-V)	4.47 (5.2.8)	5.2.8	3	1	-	-	4	-	1/1	-	x	¹⁾ X	-	-	-	x	x	
Axis 221	4.30 (5.2.8) 4.40 (5.2.8) 4.45 (5.2.8)	5.2.8	3	1	-	-	4	-	2/1	-	-	¹⁾ X	-	-	-	x	x	
Axis 223M	4.45 (5.2.8)	5.2.8	3	1	-	-	4	-	2/1	-	x	¹⁾ X	-	-	-	x	x	Pan/Tilt via RS485
Axis 225FD	4.31 (5.2.8) 4.45 (5.2.8)	5.2.8	3	1	-	-	4	-	2/1	-	-	¹⁾ X	-	-	-	x	x	
Axis 231 (D+)	4.40 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	¹⁾ X	-	-	-	x	x	
Axis 232 (D+)	4.40.2 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	¹⁾ X	-	-	-	x	x	
Axis 233D	4.42 (5.2.8) 4.48 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	x	¹⁾ X	-	-	-	x	x	
Axis 240Q	4.20 (5.2.8)	5.2.8	3	-	-	-	3	-	4/4	x	-	²⁾ X	-	-	-	x	-	
Axis 241Q	4.30 (5.2.8) 4.40 (5.2.8) 4.47 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	²⁾ X	-	-	-	x	x	
Axis 241QA	4.30.2 (5.2.8) 4.47 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	²⁾ X	-	-	-	x	x	
Axis 241S	4.20.1 (5.2.8) 4.30 (5.2.8) 4.40.1 (5.2.8) 4.47 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	¹⁾ X	-	-	-	x	x	
Axis 241SA	4.30 (5.2.8) 4.30.2 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	x	¹⁾ X	-	-	-	x	x	
Axis 243Q-Blade	4.45 (5.2.8) 4.46 (5.2.8)	5.2.8	3	1	-	-	4	-	4/4	x	-	¹⁾ X	-	-	-	x	x	
Axis 243SA		5.2.8	3	1	-	-	4	-	4/4	x	x	¹⁾ X	-	-	-	x	x	
Axis 247S		5.2.9	3	1	-	-	4	-	1/1	x	x	¹⁾ X	-	-	-	x	x	
Axis 282		5.2.12	3	1	-	-	4	-	4/4	x	-	¹⁾ X	-	-	-	x	x	
Axis 282A		5.2.12	3	1	-	-	4	-	4/4	x	x	¹⁾ X	-	-	-	x	x	
Axis 2100	2.43 (5.2.8)	5.2.8	3	-	-	-	3	-	1/1	-	-	-	-	-	-	-	-	
Axis 2110	2.43 (5.2.8)	5.2.8	3	-	-	-	3	-	1/1	-	-	-	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Axis 2120	2.43 (5.2.8)	5.2.8	3	-	-	-	3	-	1/1	-	-	-	-	-	-	-	-	
Axis 2130	2.43 (5.2.8)	5.2.8	3	-	-	-	3	-	1/1	x	-	-	-	-	-	-	-	
Axis 2130R		5.2.8	3	-	-	-	3	-	1/1	x	-	-	-	-	-	-	-	
Axis 2400		5.2.8	3	-	-	-	3	-	4/1	x	-	-	-	-	-	-	-	
Axis 2401		5.2.8	3	-	-	-	3	-	4/1	x	-	-	-	-	-	-	-	
Axis 2411		5.2.8	3	-	-	-	3	-	-/-	x	-	-	-	-	-	-	-	
Axis 2420 (IR)	2.43 (5.2.8)	5.2.8	3	-	-	-	3	-	1/1	-	-	-	-	-	-	-	-	
Axis M1011		5.2.11	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M1011-W	5.00 (5.2.11)	5.2.11	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M1031-W	5.00 (5.2.11)	5.2.11	3	-	3	-	6	-	-/-	-	x	¹ X	-	¹ X	-	x	x	
Axis M1054	5.15.1 (5.3.5)	5.3.5	3	-	3	-	6	-	1/1	-	x	¹ X	-	¹ X	-	x	x	
Axis M1103	5.08.1 (5.3.5)	5.3.5	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M1104	5.08.1 (5.3.5)	5.3.5	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M1113(-E)	5.08.1 (5.3.5)	5.3.5	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M1114(-E)	5.08.1 (5.3.5)	5.3.5	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3011	5.01 (5.2.12)	5.2.12	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3014	5.05 (5.3.0)	5.3.0	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3113(-R)(-VE)	5.11 (5.3.4)	5.3.4	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3114(-R)(-VE)	5.11 (5.3.4)	5.3.4	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3203(-V)	5.11 (5.3.4)	5.3.4	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M3204(-V)	5.11 (5.3.4)	5.3.4	3	-	3	-	6	-	-/-	-	-	¹ X	-	¹ X	-	x	x	
Axis M7001	5.02 (5.2.12)	5.2.12	1	-	1	-	2	-	-/-	x	-	¹ X	-	¹ X	¹ X	x	x	
Axis P1311	5.01 (5.2.12)	5.2.12	3	-	3	-	6	-	1/1	-	x	¹ X	-	¹ X	-	x	x	
Axis P1343(-E)	5.06 (5.3.1)	5.3.1	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P1344(-E)	5.06 (5.3.2)	5.3.2	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P1346(-E)	5.06 (5.3.2) 5.22 (5.3.9) 5.40.1 (5.4.0)	5.3.2	3	-	3	-	6	x	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P1347(-E)	5.11 (5.3.6) 5.22 (5.4.0)	5.3.6	3	-	3	-	6	x	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P3301(-V)	5.01 (5.2.9)	5.2.9	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P3304(-V)	5.12 (5.3.6)	5.3.6	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P3343(-V)(-VE)	5.05 (5.2.14)	5.2.14	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P3344(-V)(-VE)	5.05 (5.2.14)	5.2.14	3	-	3	-	6	-	1/1	-	x	¹ X	³ X	¹ X	-	x	x	Analytics: "AXIS Cross Line Detection"
Axis P3346(-V)(-VE)	5.20 (5.3.8)	5.3.8	3	-	3	-	6	x	1/1	-	x	¹ X	-	¹ X	-	x	x	
Axis P5512	5.25 (5.4.1)	5.4.1	3	-	3	-	6	-	4**	x	x	¹X	-	-	-	x	x	
Axis P5512-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹X	-	-	-	x	x	
Axis P5522		5.4.1	3	-	3	-	6	-	4**	x	x	¹X	-	-	-	x	x	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*				VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG											
Axis P5522-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	
Axis P5532	5.15 (5.3.7)	5.3.7	3	-	3	-	6	-	4**	x	x	¹⁾ x	-	-	x	x	
Axis P5532-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	
Axis P5534	5.15 (5.3.2)	5.3.2	3	-	3	-	6	-	4**	x	x	¹⁾ x	-	-	x	x	
Axis P5534-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	
Axis P8221	5.10.1 (5.4.0)	5.4.0	-	-	-	-	-	-	8**	-	-	-	-	-	-	-	
Axis Q1755(-E)	5.02 (5.2.11)	5.2.11	3	-	3	-	6	-	2**	x	x	¹⁾ x	-	¹⁾ x	-	x	PTZ: Zoom only
Axis Q1910	5.11 (5.3.4)	5.3.4	3	-	3	-	6	-	2**	-	x	¹⁾ x	³⁾ x	¹⁾ x	-	x	Pan/Tilt via RS485 Analytics: "AXIS Cross Line Detection"
Axis Q1921	5.11 (5.3.7)	5.3.7	3	-	3	-	6	-	2**	-	x	¹⁾ x	³⁾ x	¹⁾ x	-	x	Pan/Tilt via RS485 Analytics: "AXIS Cross Line Detection"
Axis Q6032	5.06 (5.2.14)	5.2.14	3	-	3	-	6	-	4**	x	x	¹⁾ x	-	-	x	x	Audio and Digital I/O support requires SeeTec version 5.4.1 or higher
Axis Q6032-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	
Axis Q6034	5.15 (5.3.5)	5.3.5	3	-	3	-	6	-	4**	x	x	¹⁾ x	-	-	x	x	
Axis Q6034-E		5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	
Axis Q6035	5.25 (5.4.1)	5.4.1	3	-	3	-	6	-	4**	x	x	¹⁾x	-	-	x	x	Up to 60 fps supported
Axis Q6035-E	5.25 (5.4.1)	5.4.1	3	-	3	-	6	-	-/-	x	-	¹⁾x	-	-	x	x	Up to 60 fps supported
Axis Q7401	5.01 (5.2.8)	5.2.8	3	-	3	-	6	-	4**	x	x	¹⁾ x	³⁾ x	¹⁾ x	x	x	Analytics: "AXIS Cross Line Detection"
Axis Q7404	5.02 (5.3.0)	5.3.0	3	-	3	-	6	-	8**	x	x	¹⁾ x	-	¹⁾ x	x	x	
Axis Q7406	5.01 (5.2.11)	5.2.11	3	-	3	-	6	-	12**	x	-	¹⁾ x	³⁾ x	¹⁾ x	x	x	Analytics: "AXIS Cross Line Detection"
Basler BIP-640c(-dn)	1.6-1 (5.3.5) 2.0-1	5.2.9	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP-1000c(-dn)	1.6-1 (5.3.5) 2.0-1	5.2.9	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP-1300c(-dn)	1.6-1 (5.3.5) 2.0-1	5.2.9	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP-1600c(-dn)	1.6-1 (5.3.5) 2.0-1	5.2.9	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP-D1000c-dn	1.6-1 (5.3.5) 2.0-1	5.3.5	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP-D1300c-dn	1.6-1 (5.3.5) 2.0-1	5.3.5	2	1	1	-	2	-	1/1	-	-	²⁾ x	-	-	-	-	Motion Detection not available for MPEG-4 Motion Detection requires Firmware 1.6-1 or higher Resolution downscaling requires SeeTec version 5.3.8 or higher
Basler BIP2-640c(-dn)	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	2/1	-	-	²⁾x	-	-	-	-	Up to 100 fps supported
Basler BIP2-1000c(-dn)	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	2/1	-	-	²⁾x	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Basler BIP2-1300c(-dn)	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	2/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-1600c(-dn)	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	2/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-1280c(-dn)	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	2/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-1920c(-dn)	3.4.2 (5.4.1)	5.4.1	2	-	2	-	2	-	2/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-2500c(-dn)	3.4.2 (5.4.1)	5.4.1	2	-	2	-	2	-	2/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-D1000c-dn	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	1/1	-	-	²⁾ X	-	-	-	-	-	
Basler BIP2-D1300c-dn	3.4.2 (5.4.1)	5.4.1	3	-	3	-	3	-	1/1	-	-	²⁾ X	-	-	-	-	-	
Beckhoff SPS		5.2.8	-	-	-	-	-	-	x/x	-	-	-	-	-	-	-	-	Number of I/Os depending on hardware
Behnke 43-621/660/714/717/752/2911	V 1.6 (5.3.2)	5.3.2	1	-	-	-	1	-	-/-	-	-	-	-	-	-	-	-	
BOSCH (VCS) VideoJet 10	2.11 (5.2.11)	5.2.11	1	2	-	-	3	-	1/1	-	-	²⁾ X	-	-	²⁾ X	-	x	
BOSCH (VCS) VideoJet 1000	2.02 (5.2.11)	5.2.11	1	2	-	-	3	-	1/1	-	-	²⁾ X	-	-	²⁾ X	-	x	
BOSCH (VCS) VIP 10	2.12 (5.2.12)	5.2.12	1	2	-	-	3	-	2/1	-	-	²⁾ X	-	-	²⁾ X	-	x	
BOSCH EX-30-IP	3.50 (5.2.12)	5.2.12	1	2	2	-	3	-	-/-	-	-	²⁾ X	-	-	-	-	x	
BOSCH EX-36-IP	3.51 (5.2.12)	5.2.12	1	2	2	-	3	-	-/-	-	-	²⁾ X	-	-	-	-	x	
BOSCH EX-80-IP	3.52 (5.2.12)	5.2.12	1	2	2	-	3	-	-/-	-	-	²⁾ X	-	-	-	-	x	
BOSCH NWC/NWD-455 (Dinion/FlexiDome)	3.51 (5.2.10) 4.00 (5.3.0) 4.10 (5.3.7)	5.2.10	1	2	2	-	3	-	1/1	-	-	²⁾ X	²⁾ X	-	-	-	x	Analytics: 1 global "IVA" trigger supported
BOSCH NWC/NWD-495 (Dinion/FlexiDome)		5.2.12	1	2	2	-	3	-	1/1	-	-	²⁾ X	²⁾ X	-	-	-	x	Analytics: 1 global "IVA" trigger supported
BOSCH NBC/NDC455, NBN/NDN-498 (Dinion/FlexiDome)	4.10.46 (5.3.5)	5.3.5	1	-	2	-	3	-	2/1	x	x	²⁾ X	²⁾ X	-	-	-	x	Analytics: 1 global "IVA" trigger supported PTZ via RS485 (Pelco-D, AutoDome) requires SeeTec version 5.4.0 or higher
BOSCH NBC/NDC-225-P, NBC/NDC-255-P	4.10 (5.3.5)	5.3.5	1	-	2	-	3	-	1/1	-	x	²⁾ X	-	-	-	-	-	Digital I/O support requires SeeTec version 5.3.7 or higher MJPEG not available before SeeTec version 5.4.0
Bosch NTC-255-PI		5.4.1	1	-	2	-	3	-	1/1	-	x	²⁾ X	-	-	-	-	-	
BOSCH NBC/NDC-265	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	1/1	-	x	²⁾ X	-	-	-	-	-	
BOSCH NBN/NDN-921 (Dinion/FlexiDome)	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	2/1	x	x	²⁾ X	²⁾ X	-	-	-	x	PTZ via RS485 (Pelco-D, AutoDome)
BOSCH VEZ-211 (Easy II IP)	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	2/1	x	-	²⁾ X	²⁾ X	-	-	-	x	
BOSCH VOT-320VxxxH	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	2/2	x	-	²⁾ X	²⁾ X	-	-	-	x	Camera Analytics: 1 global "IVA" trigger supported PTZ via RS485 (Pelco-D, AutoDome)
BOSCH VOT-320VxxxL	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	2/2	x	-	²⁾ X	²⁾ X	-	-	-	x	Camera Analytics: 1 global "IVA" trigger supported PTZ via RS485 (Pelco-D, AutoDome)
BOSCH VJR-811 (AutoDome Junior HD)	4.53 (5.4.1)	5.4.1	1	-	2	-	3	-	2/1	x	x	²⁾ X	²⁾ X	-	-	-	x	Camera Analytics: 1 global "IVA" trigger supported
BOSCH VG4 (AutoDome)	3.50 (5.2.11)	5.2.11	1	2	2	-	3	-	-/-	x	-	²⁾ X	²⁾ X	-	-	-	x	Support for Motion Detection requires SeeTec Version 5.4.1 or higher Camera Analytics: 1 global "IVA" trigger supported

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*				VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes	
			MJPEG	MPEG-4	H.264	MxPEG												total
BOSCH VG4 (AutoDome H.264-Generation)	4.10 (5.3.7)	5.3.7	1	-	2	-	3	-	-/-	x	-	²⁾ X	²⁾ X	-	-	-	x	Support for Motion Detection requires SeeTec Version 5.4.1 or higher Camera Analytics: 1 global "IVA" trigger supported
BOSCH VG5-825 (AutoDome HD)	4.53 (5.4.0)	5.4.0	1	-	2	-	3	-	2/1	x	x	²⁾ X	²⁾ X	-	-	-	x	Camera Analytics: 1 global "IVA" trigger supported
BOSCH VideoJet X10 (SN)	3.50 (5.2.12) 3.53 4.00	5.2.12	1	2	2	-	3	-	4/4	x	x	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported
BOSCH VideoJet X20 (SN)	3.51 (5.2.10) 3.53 4.00	5.2.10	1	2	2	-	3	-	4/4	x	x	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported
BOSCH VideoJet X40 (SN)	3.52 (5.2.12) 3.53 4.00	5.2.12	1	2	2	-	3	-	4/4	x	x	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported
BOSCH VIP X1	2.52 (5.2.12)	5.2.12	1	2	-	-	3	-	4/1	x	-	²⁾ X	-	-	²⁾ X	-	x	
BOSCH VIP X1 XF	4.11 (5.3.7)	5.3.7	1	-	2	-	3	-	2/2	x	x	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported
BOSCH VIP X2	2.52 (5.2.12)	5.2.12	1	2	-	-	3	-	4/1	x	x	²⁾ X	-	-	²⁾ X	-	x	
BOSCH VIPX1600M4S	3.52 (5.2.12) 4.00 (5.3.0) 4.10	5.2.12	1	2	2	-	3	-	4/4	x	-	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported
BOSCH VIP-X1600-XFM4	4.00 (5.3.2) 4.10 4.20	5.3.2	1	-	2	-	3	-	1/1	x	x	²⁾ X	²⁾ X	-	²⁾ X	-	x	AutoDome PTZ protocoll requires SeeTec version 5.3.8 or higher Analytics: 1 global "IVA" trigger supported Audio support requires SeeTec version 5.4.0 or higher
Commend B_CP_CAM		5.2.10	1	-	-	-	1	-	-/-	-	-	-	-	-	-	-	-	
Convision CC-6000	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Convision CC-6004	V1.103C-003 (5.4.0)	5.4.0	-	-	1	-	1	-	4/4	x	x	¹⁾ X	-	-	-	-	-	
Convision CC-6306/6357/6362	V1.104A-013 (5.3.5)	5.3.5	-	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
Convision CC-6331/6337/6400	V1.103H-044 (5.3.5)	5.3.5	-	-	1	-	1	-	4/2	x	x	¹⁾ X	-	-	-	-	-	
Convision CC-6353/6358		5.3.5	-	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
Convision CC-6355/6361	V1.104A-013 (5.3.5)	5.3.5	-	-	1	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Convision CC-7131	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
Convision CC-7200	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	1/1	x	x	¹⁾ X	-	-	-	-	-	PTZ: Zoom only
Convision V400		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V410		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V600	4.7.2 (5.2.8)	5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V610		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V800		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V1200		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V1600		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	
Convision V4000		5.2.8	1	-	-	-	1	-	4/4	-	-	-	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*				VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes	
			MJPEG	MPEG-4	H.264	MxPEG												total
Dallmeier DF-3000IP	2.1.3 (5.2.9) 2.3.3 2.4.4 2.4.9	5.2.9	-	1	-	-	1	-	-/-	-	-	-	-	-	-	-	Firmware version 2.4.2 not supported	
Dallmeier DDF-3000IPV	2.1.3 (5.2.9) 2.3.0 2.4.4	5.2.9	-	1	-	-	1	-	-/-	-	-	-	-	-	-	-	Firmware version 2.4.2 not supported	
Dallmeier Microstreamer	2.3.0 (5.3.1)	5.3.1	-	1	-	-	1	-	-/-	-	-	-	-	-	-	-	Firmware version 2.4.2 not supported	
Ganz ZN-NH21VE	1.02.03 (5.3.7)	5.3.7	1	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	x	-	MJPEG framerate for live view should not be higher than for recording Support for MJPEG megapixel resolutions requires SeeTec version 5.3.8 or higher
Ganz ZN-S1000VE	1.06.00 (5.3.6)	5.3.6	1	1	1	-	1	-	2/2	x	x	¹⁾ X	³⁾ X	-	-	x	-	Analytics: 1 global trigger supported for all zones and rules
Ganz ZN-VS801P	3.2.54_C (5.3.7)	5.3.7	1	1	-	-	1	-	2/2	-	-	²⁾ X	-	-	-	-	-	
Grandeye Halocam IPC	00.29.2 (5.2.8) 0.39.14	5.2.8	1	-	-	-	1	-	-	x	-	¹⁾ X	-	-	-	-	-	Dewarping + Virtual PTZ on camera and in SeeTec 5 software supported Motion Detection only available in fisheye mode
Grandeye Halocam IPW		5.2.8	1	-	-	-	1	-	-	x	-	¹⁾ X	-	-	-	-	-	Dewarping + Virtual PTZ on camera and in SeeTec 5 software supported Motion Detection only available in fisheye mode
Hikvision DS-2CD7133-E	V2.0 (5.3.5) V3.0 (5.3.9)	5.3.5	-	-	1	-	1	-	-/-	x	-	¹⁾ X	-	-	-	-	-	Motion Detection support requires SeeTec version 5.4.0 or higher
Hikvision DS-2CD7153-E	V2.0 (5.3.5) V3.0 (5.3.6)	5.3.5	-	-	1	-	1	-	-/-	x	-	¹⁾ X	-	-	-	-	-	Motion Detection support requires SeeTec version 5.4.0 or higher
Hikvision DS-2CD853F-E	V3.0 (5.3.5)	5.3.8	-	-	1	-	1	-	1/1	x	x	¹⁾ X	-	-	-	-	-	Digital I/Os, Motion Detection and Audio support requires SeeTec version 5.4.0 or higher
Hikvision DS-2DF1-570A/57A/573A	V1.0.0beta (5.3.9) V1.0.0beta (5.4.0)	5.3.9	2	-	2	-	2	-	1/1	x	x	¹⁾ X	-	-	-	-	-	This device is tested with beta firmware V1.0.0 101218 only. Please contact SeeTec support if firmware is needed. MJPEG, Multistreaming, Digital I/Os, Motion Detection and Audio support requires SeeTec version 5.4.0 or higher
Hikvision DS-2DF1-5702/572/5732	V4.0.0 (5.4.1)	5.4.1	-	-	2	-	2	-	1/1	x	x	¹⁾ X	-	-	-	-	-	
Hikvision DS-2CD886	V2.0 (5.4.1)	5.4.1	-	-	1	-	1	-	4/3	-	x	¹⁾ X	-	-	-	-	-	
Hikvision DS-2CD762/862	V2.0 (5.4.1)	5.4.1	-	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
IQinVision IQD30	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	
IQinVision IQD31	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	
IQinVision IQD32	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	
IQinVision IQM30	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	
IQinVision IQM31	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	
IQinVision IQM32	V3.2/4 (5.3.8) V3.3/1 (5.4.0)	5.3.8	1	-	1	-	1	-	-/-	-	x	²⁾ X	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
IQinVision IQ040	V3.0/2 (5.2.12) 3.0/407 3.0/6 3.0/9	5.2.12	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQ041	V3.0/2 (5.2.12) 3.0/407 3.0/6 3.0/9	5.2.12	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQ042	V3.0/2 (5.2.12) 3.0/407 3.0/6 3.0/9	5.2.12	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQD40	3.0/6 (5.2.14)	5.2.14	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQD41	3.0/6 (5.2.14)	5.2.14	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQD42	3.0/6 (5.2.14)	5.2.14	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Only maximum resolution available. Lower resolutions can only be cropped.
IQinVision IQ510	V2.8/6 (5.2.8)	5.2.8	1	-	-	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher
IQinVision IQ511	V2.8/6 (5.2.8)	5.2.8	1	-	-	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher
IQinVision IQ540	V3.0/8 (5.3.2)	5.3.2	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher
IQinVision IQ541	V3.0/8 (5.3.2)	5.3.2	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher
IQinVision IQ542	V3.0/8 (5.3.2)	5.3.2	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher
IQinVision IQ711/751	V2.8/6 (5.2.8) V3.0/2 V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ702/752	V2.8/6 (5.2.8) V3.0/2 V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ703/753	V2.8/6 (5.2.8) V3.0/2 V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹⁾ X	-	-	-	-	-	cropping supported resolution not changeable before version 5.2.9 Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware Digital I/O support requires SeeTec Version 5.3.2 or higher
IQinVision IQ705/755	V2.8/6 (5.2.8) V3.0/2 V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹⁾ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ732	V3.1/8 (5.3.7) 3.2/4 (5.3.8) V3.0/9 (5.3.9)	5.3.7	1	-	1	-	1	-	1/1	-	x	²⁾ X	-	-	-	-	-	Firmware version 3.2/3 or higher requires SeeTec Version 5.3.8 or higher Motion Detection requires activated standard recording

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
IQinVision IQ811/851 Sentinel	V2.8/6 (5.2.8) V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ802/852 Sentinel	V2.8/6 (5.2.8) V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ803/853 Sentinel	V2.8/6 (5.2.8) V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ805/855 Sentinel	V2.8/6 (5.2.8) V3.0/9 (5.3.9)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQ832 Sentinel	3.2/4 (5.3.8)	5.3.8	1	-	1	-	1	-	1/1	-	-	² X	-	-	-	-	-	
IQinVision IQA10 Alliance	V2.9/6 (5.2.8) V3.1/1(5.4.0)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQA11 Alliance	V2.9/6 (5.2.8) V3.0/9 (5.3.9) V3.1/1(5.4.0)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQA12 Alliance	V2.9/6 (5.2.8) V3.0/9 (5.3.9) V3.1/1(5.4.0)	5.2.8	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQA13 Alliance	V2.9/6 (5.2.14) V3.0/9 (5.3.9) V3.1/1(5.4.0)	5.2.14	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
IQinVision IQA15 Alliance	V2.9/6 (5.2.14) V3.0/9 (5.3.9) V3.1/1(5.4.0)	5.2.14	1	-	-	-	1	-	1/1	-	-	¹ X	-	-	-	-	-	cropping supported Motion Detection requires Firmware V2.8/6 or higher ViaSys plugin requires special firmware
JVC VN-V25U		5.2.10	1	1	-	-	1	-	2/2	-	-	¹ X	-	-	-	-	-	
JVC VN-V26U		5.2.10	1	1	-	-	1	-	2/2	-	-	¹ X	-	-	-	-	-	
JVC VN-V685U/V686(WP)(B)U		5.2.10	1	1	-	-	1	-	2/2	x	-	¹ X	-	-	-	-	-	
JVC VN-X35U	0.32 (5.2.10)	5.2.10	1	1	-	-	1	-	2/2	-	-	¹ X	-	-	-	-	-	
JVC VN-V225(VP)U	1.00 (5.2.10)	5.2.10	1	1	-	-	1	-	2/2	-	-	¹ X	-	-	-	-	-	
JVC VN-X235(VP)U	1.00 (5.2.10)	5.2.10	1	1	-	-	1	-	2/2	-	-	¹ X	-	-	-	-	-	
Lumenera Li045		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le045		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le075		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le165		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le175		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le259		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le275		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	
Lumenera Le375		5.2.8	1	-	-	-	1	-	-/-	-	-	¹ X	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Lumenera Le575		5.2.8	1	-	-	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Lumenera Le11059		5.2.8	1	-	-	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
Mobotix M1		5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	-	-	
Mobotix M10	M10-V2.2.3.24 (5.2.8)	5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	-	-	
Mobotix M12	MX-V3.3.1.7 (5.2.8)	5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	x	-	cropping supported
Mobotix D12		5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	x	-	cropping supported
Mobotix M22	MX-V3.3.2.3 (5.2.8)	5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	x	-	cropping supported
Mobotix M24	MX-V4.0.2.33 (5.3.4)	5.3.4	1	-	-	1	1	-	-/-	x	-	³⁾ X	-	-	-	x	-	cropping supported Camera OnBoard Virtual PTZ support requires SeeTec version 5.3.5 or higher
Mobotix T24	MX-V4.0.4.18 (5.3.8)	5.3.8	1	-	-	1	1	-	-/-	x	-	³⁾ X	-	-	-	x	-	Camera OnBoard Virtual PTZ supported
Mobotix D22		5.2.8	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	x	-	cropping supported
Mobotix D24		5.3.2	1	-	-	1	1	-	-/-	-	-	³⁾ X	-	-	-	x	-	cropping supported
Mobotix Q22		5.2.14	1	-	-	1	1	-	-/-	x	-	³⁾ X	-	-	-	x	-	
Mobotix Q24	MX-V4.0.1.5 (5.2.14)	5.2.14	1	-	-	1	1	-	-/-	x	-	³⁾ X	-	-	-	x	-	
Panasonic BB-HCE481		5.2.8	1	-	-	-	1	-	-/-	x	-	-	-	-	-	-	-	
Panasonic BB-HCM311/331		5.2.8	1	-	-	-	1	-	2/1	x	-	-	-	-	-	-	-	
Panasonic BB-HCM381/481		5.2.8	1	-	-	-	1	-	2/1	x	-	-	-	-	-	-	-	
Panasonic BB-HCM403		5.2.8	1	-	-	-	1	-	2/1	-	-	-	-	-	-	-	-	
Panasonic BB-HCM511/531	3.12R0 (5.2.8) 3.14R01 3.20R01	5.2.8	1	1	-	-	1	-	2/1	x	x	-	-	-	-	-	-	
Panasonic BB-HCM515	3.14R03 (5.2.8)	5.2.8	1	1	-	-	1	-	2/1	x	x	-	-	-	-	-	-	
Panasonic BB-HCM527		5.2.9	1	1	-	-	1	-	2/1	-	x	-	-	-	-	-	-	
Panasonic BB-HCM580/581	3.14R01 (5.2.8)	5.2.8	1	1	-	-	1	-	2/1	x	x	-	-	-	-	-	-	
Panasonic BL-C1/20		5.2.8	1	-	-	-	1	-	-/-	-	-	-	-	-	-	-	-	
Panasonic BL-C10/30		5.2.8	1	-	-	-	1	-	-/-	x	-	-	-	-	-	-	-	
Panasonic BL-C101	3.60R00 (5.4.1)	5.4.1	1	1	-	-	1	-	1/-	-	-	-	-	-	-	-	-	
Panasonic BL-C111/131		5.2.8	1	1	-	-	1	-	-/-	x	x	-	-	-	-	-	-	Hardware Motion Sensor can be configured as digital input
Panasonic BL-C121		5.4.1	1	1	-	-	1	-	1/1			-	-	-	-	-	-	
Panasonic BL-C140/160	3.60R00 (5.4.1)	5.4.1	1	1	-	-	1	-	-/-			-	-	-	-	-	-	
Panasonic BL-C210		5.4.1	1	1	-	-	1	-	2/-	x		-	-	-	-	-	-	
Panasonic BL-C230	4.31R00 (5.4.1)	5.4.1	1	1	-	-	1	-	2/1	x		-	-	-	-	-	-	
Panasonic KX-HCM10		5.2.8	1	-	-	-	1	-	-/-	x	-	-	-	-	-	-	-	
Panasonic KX-HCM230		5.2.8	1	-	-	-	1	-	1/1	x	-	-	-	-	-	-	-	
Panasonic KX-HCM280		5.2.8	1	-	-	-	1	-	1/1	x	-	-	-	-	-	-	-	
Panasonic WJ-GXE500	1.03 (5.3.8)	5.3.8	1	-	2	-	3	-	3/1	x	x	³⁾ X	-	-	-	-	-	H.264 Stream parameters have to be set manually on the encoder

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Panasonic WJ-NT304		5.2.8	1	1	-	-	1	-	4/4	x	-	³ X	-	-	-	-	-	resolution/compression not changeable PTZ: Panasonic protocol
Panasonic WJ-NT314		5.2.9	1	1	-	-	1	-	4/4	x	-	³ X	-	-	-	-	-	resolution/compression not changeable PTZ: Panasonic protocol
Panasonic WV-NF284	1.02E0 (5.2.8) 1.10E7	5.2.8	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NF302	1.03 (5.2.8) 1.10EA	5.2.8	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NM100		5.2.8	1	1	-	-	1	-	-/-	x	-	³ X	-	-	-	-	-	
Panasonic WV-NP1000/1004	1.21E0 (5.2.8)	5.2.8	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NP240/244	1.25E3 (5.2.8) 1.30E7	5.2.8	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NP304	1.10EA (5.2.9)	5.2.9	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NP472		5.2.8	1	1	-	-	1	-	-/-	-	-	³ X	-	-	-	-	-	
Panasonic WV-NP502	1.01E1 (5.2.14) 1.10 (5.3.8)	5.2.14	1	-	2	-	3	-	3/1	-	x	¹ X	-	-	-	-	-	Multistreaming support requires version 5.3.8 or higher Support for 16:9 resolutions requires firmware 1.10 or higher and SeeTec version 5.3.8 or higher Motion Detection via method 1) requires SeeTec version 5.3.8 or higher
Panasonic WV-NS202	1.11P2 (5.2.8) 2.20PM 2.50PB	5.2.8	1	1	-	-	1	-	-/1	x	x	³ X	-	-	-	-	-	
Panasonic WV-NS320		5.2.8	1	1	-	-	1	-	-/-	x	-	³ X	-	-	-	-	-	
Panasonic WV-NS950/NS954; WV-NW960/NW964	1.06E0 (5.2.8) 1.10EB	5.2.8	1	1	-	-	1	-	-/1	x	x	³ X	-	-	-	-	-	
Panasonic WV-NW470		5.2.8	1	1	-	-	1	-	-/-	-	-	³ X	-	-	-	-	-	
Panasonic WV-NW474		5.2.8	1	1	-	-	1	-	-/-	x	-	³ X	-	-	-	-	-	
Panasonic WV-NW484	110ED (5.2.8)	5.2.8	1	1	-	-	1	-	1/1	-	x	³ X	-	-	-	-	-	
Panasonic WV-NW502	0.8ZE6 (5.2.13) 1.01E1 1.10 (5.3.8)	5.2.13	1	-	2	-	3	-	3/1	-	x	¹ X	-	-	-	-	-	Multistreaming support requires version 5.3.8 or higher Support for 16:9 resolutions requires firmware 1.10 or higher and SeeTec version 5.3.8 or higher Motion Detection via method 1) requires SeeTec version 5.3.8 or higher
Panasonic WV-SC385/SW395	1.04 (5.3.8)	5.3.8	1	-	2	-	3	-	1/1	x	x	¹ X	-	-	-	-	-	
Panasonic WV-SP302/SF332//SF342	1.04 (5.3.8)	5.3.8	1	-	2	-	3	-	1/1	-	x	¹ X	-	-	-	-	-	
Panasonic WV-SP305/SP306/SF335/SF336/SF346	1.03 (5.3.8) 1.04 (5.3.8)	5.3.8	1	-	2	-	3	-	1/1	-	x	¹ X	-	-	-	-	-	
Panasonic WV-SP102	1.01 (5.3.8)	5.3.8	1	-	2	-	3	-	-/-	-	-	¹ X	-	-	-	-	-	
Panasonic WV-SP105	1.01 (5.3.8)	5.3.8	1	-	2	-	3	-	-/-	-	-	¹ X	-	-	-	-	-	
PCS Convision CC-6000	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	2/2	x	x	¹ X	-	-	-	-	-	
PCS Convision CC-6004	V1.103C-003 (5.4.0)	5.4.0	-	-	1	-	1	-	4/4	x	x	¹X	-	-	-	-	-	
PCS Convision CC-6306/6357/6362	V1.104A-013 (5.3.5)	5.3.5	-	-	1	-	1	-	1/1	-	x	¹ X	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
PCS Convision CC-6331/6337/6400	V1.103H-044 (5.3.5)	5.3.5	-	-	1	-	1	-	4/2	x	x	¹⁾ X	-	-	-	-	-	
PCS Convision CC-6353/6358		5.3.5	-	-	1	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
PCS Convision CC-6355/6361	V1.104A-013 (5.3.5)	5.3.5	-	-	1	-	1	-	-/-	-	-	¹⁾ X	-	-	-	-	-	
PCS Convision CC-7131	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	1/1	-	x	x	-	-	-	-	-	
PCS Convision CC-7200	V1.103A-034 (5.3.9)	5.3.9	-	-	1	-	1	-	1/1	x	x	x	-	-	-	-	-	PTZ: Zoom only
Pelco ID10x/IX10x/IE10x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IDE10x/IXE10x/IEE10x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IDE20x/IXE20x/IEE20x	1.7.19 (5.4.1)	5.4.0	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco ID30x/IX30x/IE30x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IDE30x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IDS0x/IXS0x/IES0x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	1/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IMS0x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	-/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco IM10x	1.7.19 (5.4.1)	5.4.1	2	-	2	-	2	-	-/1	-	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco S5118 Spectra HD	1.7.19 (5.4.0)	5.4.0	2	-	2	-	2	-	-/1	x	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco SD427/425/4H35 Spectra IV IP		5.4.1	2	-	2	-	2	-	-/2	x	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Pelco SD423 Spectra IV IP	1.7.24 (5.4.1)	5.4.1	2	-	2	-	2	-	-/1	x	x	-	-	-	-	-	-	Parameters for second stream have to be configured manually on the camera
Samsung SNB-2000	1.40 (5.4.0)	5.4.0	1	-	1	-	2	-	2/2	-	-	¹⁾ X	-	-	-	x	-	
Samsung SNB-3000	1.40 (5.4.0)	5.4.0	1	-	1	-	2	-	1/1	-	x	¹⁾ X	-	-	-	-	-	Analytics: 1 global trigger supported
Samsung SNB-5000	2.00 (5.4.1)	5.4.1	1	-	1	-	2	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
Samsung SNB-7000	1.00 (5.4.0)	5.4.0	1	-	1	-	2	-	1/1	-	x	¹⁾ X	-	-	-	-	-	
Samsung SND-3080	1.10 (5.3.6)	5.3.6	1	-	1	-	1	-	2/2	-	-	¹⁾ X	-	-	-	-	-	
Samsung SND-5080	1.10 (5.3.7) 2.00(5.4.1)	5.3.7	1	-	1	-	2	-	1/1	-	x	¹⁾ X	¹⁾ X	-	-	-	-	Analytics: 1 global trigger supported Motion Detection Support requires SeeTec Version 5.4.1 or higher Multistreaming Support requires SeeTec Version 5.4.1 or higher
Samsung SNO-5080R	1.00 (5.4.0)	5.4.0	1	-	1	-	2	-	1/1	-	-	¹⁾ X	-	-	-	-	-	
Samsung SNP-3120	1.24 (5.4.1)	5.4.0	1	-	1	-	2	-	2/2	x	x	¹⁾ X	-	-	-	x	-	
Samsung SNP-3430	1.07 (5.3.9) 1.07 (5.4.1)	5.3.9	1	-	1	-	2	-	-/4	x	-	¹⁾ X	¹⁾ X	-	-	-	-	Analytics: 1 global trigger supported Multistreaming Support requires SeeTec Version 5.4.1 or higher
Samsung SNP-5190/5200	1.02 (5.4.1)	5.4.1	1	-	1	-	2	-	4/2	x	x	¹⁾ X	-	-	-	-	-	
Samsung SNV-3080	1.10 (5.3.6)	5.3.6	1	-	1	-	1	-	2/2	-	-	-	¹⁾ X	-	-	-	-	Analytics: 1 global trigger supported

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*				VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes	
			MJPEG	MPEG-4	H.264	MxPEG												total
Samsung SNV-3120	1.20 (5.4.1)	5.4.1	1	-	1	-	2	-	1/1	-	x	¹⁾ x	-	-	-	x	-	
Samsung SNV-5010	1.10 (5.4.1)	5.4.1	1	-	1	-	2	-	-/-	-	-	¹⁾ x	-	-	-	x	-	
Samsung SNV-5080(R)	1.10 (5.3.7) 1.00 (R) (5.4.1)	5.3.7	1	-	1	-	2	-	1/1	-	x	¹⁾ x	¹⁾ x	-	-	-	-	Analytics: 1 global trigger supported Multistreaming Support requires SeeTec Version 5.4.1 or higher
Samsung SNV-7080	1.01 (5.4.1)	5.4.1	1	-	1	-	2	-	1/1	-	x	¹⁾ x	-	-	-	x	-	
Samsung SNZ-5200	1.02 (5.4.0)	5.4.0	1	-	1	-	2	-	1/1	-	x	¹⁾ x	-	-	-	x	-	
Samsung SPE-100	1.30 (5.4.1)	5.4.1	1	-	1	-	1	-	1/1	-	x	¹⁾ x	-	-	-	x	-	
Samsung SPE-400	1.19 (5.4.1)	5.4.1	1	-	1	-	1	-	1/1	-	x	¹⁾ x	-	-	-	x	-	
Santec SVE-ST100SA	1.02.02 (5.3.7)	5.3.7	1	-	1	-	1	-	1/1	-	x	¹⁾ x	³⁾ x	-	-	-	-	Analytics: 1 global trigger supported for all zones and rules
Santec SVE-ST1000SA	1.02.02 (5.3.2) 1.02.03 1.06.00	5.3.2	1	1	1	-	1	-	2/2	x	x	¹⁾ x	³⁾ x	-	-	x	-	Analytics: 1 global trigger supported for all zones and rules
Santec SVE-ST4003B	1.02.02 (5.3.2) 1.02.03	5.3.2	1	1	1	-	1	-	4/2	x	x	¹⁾ x	³⁾ x	-	-	x	-	PTZ only available on Channel 1 Analytics: 1 global trigger supported for all zones and rules
Santec SVE-ST4010B	1.02.02 (5.3.2)	5.3.2	1	1	1	-	1	-	4/2	x	x	¹⁾ x	³⁾ x	-	-	x	-	PTZ only available on Channel 1 Analytics: 1 global trigger supported for all zones and rules
Sanyo VCC-HD2100	2.03-00 (5.3.9)	5.3.2	1	-	1	-	2	-	2/2	-	-	²⁾ x	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Sanyo VCC-HD2300	1.00-14 (5.3.2) 1.02-01 2.03-00 (5.3.9)	5.3.2	1	-	1	-	2	-	2/2	-	-	²⁾ x	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Sanyo VCC-HD2500	1.00-10 (5.3.2) 1.02-01 2.02-02 (5.3.9)	5.3.2	3	-	4	-	4	-	2/2	-	x	²⁾ x	²⁾ x	-	-	x	-	Multistreaming support requires version 5.3.7 or higher Before version 5.3.8 the total number of streams was limited to 2 Analytics: 1 global trigger supported
Sanyo VDC-HD3100	2.03-00 (5.3.9)	5.3.2	1	-	1	-	2	-	2/2	-	-	²⁾ x	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Sanyo VDC-HD3300	2.03-00 (5.3.9)	5.3.2	1	-	1	-	2	-	2/2	-	-	²⁾ x	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Sanyo VDC-HD3500	2.02-02 (5.3.9)	5.3.2	3	-	4	-	4	-	2/2	-	x	²⁾ x	²⁾ x	-	-	x	-	Multistreaming support requires version 5.3.7 or higher Before version 5.3.8 the total number of streams was limited to 2 Analytics: 1 global trigger supported
Sanyo VCC-HD4000	1.02-02 (5.2.12) 1.03-00 1.04-00	5.2.12	1	-	1	-	1	-	-/-	x	-	²⁾ x	-	-	-	-	-	PTZ: Zoom only
Sanyo VCC-HD4600	1.00-04 (5.3.2) 1.03-01	5.3.2	3	-	4	-	4	-	2/2	x	x	²⁾ x	²⁾ x	-	-	x	-	PTZ: zoom only Multistreaming support requires version 5.3.7 or higher Before version 5.3.8 the total number of streams was limited to 2 Analytics: 1 global trigger supported
Sanyo VCC-HD5400	1.00-03 (5.3.3) 1.03-01	5.3.3	3	-	4	-	4	-	-/-	x	x	²⁾ x	²⁾ x	-	-	x	-	Multistreaming support requires version 5.3.7 or higher Before version 5.3.8 the total number of streams was limited to 2 Analytics: 1 global trigger supported
Sanyo VCC-HD5600	1.00-01 (5.3.3) 1.03-01	5.3.3	3	-	4	-	4	-	-/-	x	x	²⁾ x	²⁾ x	-	-	x	-	Multistreaming support requires version 5.3.7 or higher Before version 5.3.8 the total number of streams was limited to 2 Analytics: 1 global trigger supported

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Sanyo VCC-XZN600P / XZ600P / ZMN600P	2.20-00 (5.2.12)	5.2.12	1	-	-	-	1	-	-/-	x	-	²⁾ X	-	-	-	-	-	PTZ: Zoom only
Sanyo VCC-N6695P	2.21-00 (5.3.6)	5.3.6	1	-	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	
Sanyo VCC-9500P/9600P/9700P/9800P	2.21-00 (5.3.6)	5.3.6	1	-	1	-	1	-	-/-	x	-	²⁾ X	-	-	-	-	-	
Schneider Intercom SI-SIP-2110	1.6 (5.2.10)	5.2.10	1	-	-	-	1	-	-	-	-	-	-	-	-	-	-	
Schneider Intercom SI-Cam 2106	1.6 (5.2.10)	5.2.10	1	-	-	-	1	-	-	-	-	-	-	-	-	-	-	
Siemens CClx1345	7.1 (5.3.7)	5.3.7	1	1	-	-	1	-	-/-	-	-	-	-	-	-	-	-	MJPEG framerate for live view should not be higher than for recording If you want to use non-default password please contact SeeTec Support
Siemens CxMx1315	X.1.1.28 (5.3.7)	5.3.7	1	1	-	-	2	-	1/-	-	-	³⁾ X	-	-	-	-	-	Digital Input notification only available via TCP trigger
Siqura S-60 E	3.3.0 (5.3.9)	5.3.9	1	-	1	-	2	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Siqura S-64 E	3.0.4 (5.3.9)	5.3.9	1	-	1	-	2	-	-/-	x	-	¹⁾ X	-	-	-	-	-	
Siqura S-68 E	3.0.4 (5.4.0)	5.4.0	1	-	1	-	2	-	-/-	x	-	¹⁾X	-	-	-	-	-	
Siqura MSD620/622 HSD620/622/626	3.12.0 (5.4.1)	5.4.1	1	-	1	-	2	-	8/1	x	-	¹⁾X	-	-	-	-	-	
Sony SNC-CH120/DH120(T)	1.35.00 (5.4.0)	5.3.6	2	-	2	-	2	-	1/1	-	x	¹⁾ X	-	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Multistreaming can not be used if multistreaming is activated
Sony SNC-CH140/DH140(T)	1.11.00 (5.3.6) 1.31.00 (5.3.9) 1.34.00 (5.3.9)	5.3.6	2	-	2	-	2	-	1/2	-	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNC-CH160/DH160	1.35.00 (5.4.0)	5.3.6	2	-	2	-	2	-	1/1	-	x	¹⁾ X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Multistreaming can not be used if multistreaming is activated
Sony SNC-CH180/DH180	1.11.00 (5.3.6) 1.31.00 (5.3.9) 1.34.00 (5.3.9)	5.3.6	2	-	2	-	2	-	1/2	-	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNC-CH110/DH110(T)	1.27.02 (5.3.9) 1.33.00 (5.4.0)	5.3.9	2	-	2	-	2	-	1/-	-	-	¹⁾ X	-	x	-	-	-	Multistreaming can not be used if multistreaming is activated
Sony SNC-CH210/DH210(T)	1.12.00 (5.3.6) 1.27.00 (5.3.9) 1.33.00 (5.4.0)	5.3.6 / 5.3.9	2	-	2	-	2	-	1/-	-	-	¹⁾ X	-	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Multistreaming can not be used if multistreaming is activated
Sony SNC-CH220/DH220	1.30.00 (5.3.9) 1.35.00 (5.4.0)	5.3.9	2	-	2	-	2	-	1/1	-	-	¹⁾ X	-	x	-	-	-	Analytics: VMF Multistreaming can not be used if multistreaming is activated
Sony SNC-CH240/DH240(T)	1.10.01 (5.3.6) 1.31.00 (5.3.9) 1.34.00 (5.3.9)	5.3.6	2	-	2	-	2	-	1/2	-	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: Tampering, VMF, Audio
Sony SNC-CH280/DH280	1.31.00 (5.3.9) 1.34.00 (5.3.9)	5.3.6	2	-	2	-	2	-	1/2	-	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNC-CM120	1.00 (5.2.10) 1.10	5.2.10	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-CS3P		5.2.8	1	-	-	-	1	-	1/2	-	-	-	-	-	-	-	-	
Sony SNC-CS10		5.2.9	1	1	-	-	1	-	1/1	-	-	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-CS11	1.01 (5.2.9)	5.2.9	1	1	-	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-CS20	1.00 (5.2.11)	5.2.11	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Sony SNC-CS50P	1.03 (5.2.8)	5.2.8	1	1	1	-	1	-	2/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DF40P	1.17 (5.2.8)	5.2.8	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-DF50P	1.11 (5.2.8)	5.2.8	1	1	1	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DF70P		5.2.8	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-DF80P		5.2.8	1	1	1	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DF85P		5.2.8	1	1	1	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DM110	1.01 (5.2.10)	5.2.10	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DM160	1.01 (5.2.10)	5.2.10	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DS10		5.2.11	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-DS60		5.2.11	1	1	-	-	1	-	1/2	-	x	¹⁾ X	-	-	-	-	-	
Sony SNC-M1		5.2.8	1	1	-	-	1	-	-/-	-	x	-	-	-	-	-	-	
Sony SNC-M3		5.2.8	1	1	-	-	1	-	-/-	x	x	-	-	-	-	-	-	
Sony SNC-P1		5.2.8	1	1	-	-	1	-	1/1	-	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-P5		5.2.8	1	1	-	-	1	-	2/1	x	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-RH124/164	1.10.01 (5.3.6) 1.31.00 (5.3.9)	5.3.6	2	-	2	-	2	-	4/2	x	x	¹⁾ X	¹⁾ X	x	-	-	-	Analytics: VMF, Audio Alarm
Sony SNC-RS44P/84P, RS46P/86P	1.10.01 (5.3.6)	5.3.6	2	-	2	-	2	-	4/4	x	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNC-RX530	3.00 (5.2.10)	5.2.10	1	1	1	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Sony SNC-RX550	1.11 (5.2.8) 2.30	5.2.8	1	1	1	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Sony SNC-RX570		5.2.10	1	1	1	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Sony SNC-RZ25P	1.29 (5.2.8)	5.2.8	1	1	-	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	Motion Detection only available for MPEG-4
Sony SNC-RZ30P		5.2.8	1	-	-	-	1	-	2/2	x	-	-	-	-	-	-	-	
Sony SNC-RZ50P	2.20 (5.2.8) 2.21	5.2.8	1	1	1	-	1	-	2/2	x	x	¹⁾ X	-	-	-	-	-	
Sony SNC-Z20P		5.2.8	1	-	-	-	1	-	1/2	x	-	-	-	-	-	-	-	PTZ: Zoom only
Sony SNT-EP104/154	1.10.01 (5.3.6) 1.31.00 (5.3.9)	5.3.6	2	-	2	-	2	-	-/-	-	-	¹⁾ X	-	-	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher
Sony SNT-EX101(E)	1.10.01 (5.3.6) 1.31.00 (5.3.9)	5.3.6	2	-	2	-	2	-	2/2	x	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNT-EX104	1.31.00 (5.3.9)	5.3.6	2	-	2	-	2	-	4/4	x	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNT-EX154	1.31.00 (5.3.9)	5.3.6	2	-	2	-	2	-	4/4	x	x	¹⁾ X	¹⁾ X	x	-	-	-	Multistreaming requires SeeTec Version 5.3.9 or higher Analytics: VMF, Audio Alarm
Sony SNT-V704	2.16 (5.2.13)	5.2.13	1	1	-	-	1	-	-/4	x	-	¹⁾ X	-	-	-	-	-	
Vivotek FD7131/7132	0102c (5.2.12) 0200d 0300a	5.2.12	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek FD7141	0100g (5.2.12)	5.2.12	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher

Device Name	Tested Firmware (in SeeTec version x)	Support from Version	No of Streams*					VCam	Digital I/O	PTZ	Audio**	VMD	Analytics	Tampering	VideoLoss	HTTPS	Multicast	Notes
			MJPEG	MPEG-4	H.264	MxPEG	total											
Vivotek IP7131/7132	0102b (5.2.12) 0200d	5.2.12	-	1	-	-	1	-	1/1	-	-	²⁾ X	-	-	-	-	-	
Vivotek IP7133/7134	0100b (5.2.14)	5.2.14	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP7135/7137	0301b (5.2.14) 0400a	5.2.14	-	1	-	-	1	-	-/-	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP7138/7139	0101h (5.2.12)	5.2.12	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP7142	0101c (5.2.12) 0300c	5.2.12	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP7151/7152	0100r (5.2.12)	5.2.12	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP7161	0101c (5.2.14) 1.03b (5.3.5)	5.2.14	2	2	-	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	Firmware Version 0103b or higher requires SeeTec version 5.3.5 or higher Multistreaming support requires version 5.3.7 or higher
Vivotek IP7330	0100f (5.2.14)	5.2.14	2	2	-	-	2	-	1/-	-	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek IP8161	0102d (5.3.7)	5.3.7	2	-	2	-	2	-	1/1	-	-	²⁾ X	-	-	-	-	-	
Vivotek PZ7111/PZ7112 /PZ7121/PZ7122	0101a (5.2.14) 0201a	5.2.14	2	2	-	-	2	-	1/1	x	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher
Vivotek SD7151	0100g (5.2.12)	5.2.12	2	2	-	-	2	-	4/1	x	-	²⁾ X	-	-	-	-	-	Multistreaming support requires version 5.3.7 or higher

Device Name	Tested Firmware	Support from Version	Device Type	Supported Features	Notes
Ordinary USB Joystick	n/a	5.3.7	Generic Direct Input game device	Joystick with up to 3 axis for PTZ control Free configurable buttons	Some Joysticks need to be calibrated in Windows before use
Axis 292	n/a	5.3.7	USB Joystick	Joystick with 3 axis for PTZ control 12 Free configurable buttons	
Axis T8311	n/a	5.3.6	USB Joystick	Joystick with 3 axis for PTZ control 6 free configurable buttons	
Axis T8312	n/a	5.3.7	USB Keypad	22 Free configurable buttons	
Axis T8313	n/a	5.3.7	USB Jog Dial	Inner and outer Jog Dial 6 free configurable buttons	
Videotec DCZ	n/a	5.3.8	USB Keypad / Joystick / Jog Dial	Joystick with 3 axis for PTZ control 32 Free configurable buttons Outer Jog Dial	Joystick needs to be calibrated in Windows before use Inner Jog Dial not supported

SeeTec 5 Supported VoIP (SIP) Devices

Device Name	Tested Firmware	Support from Version	door opener	Audio Protocol (full-duplex)	Notes
Any device using SIP standard		5.2.8	x	SIP	Door opener can be used if it can be triggered by a DTMF sequence
Baudisch SIP-Intercom-Terminal		5.2.8	x	SIP	
Behnke SIP-Intercom-Terminal		5.2.8	x	SIP	
CommendSIP-Intercom-Terminal		5.2.8	x	SIP	
CyberData VoIP Loudspeaker Amplifier		5.2.8	-	SIP	
Mobotix IP Cameras		5.2.8	x	SIP	
VoIP Intercom	102	5.2.8	x	SIP	
Schneider Intercom SI-SIP 2100		5.2.8	x	SIP	
Schneider Intercom SI-SIP2110		5.2.8	x	SIP	

SeeTec 5 Supported VoIP (SIP) Servers

Sip Server	Tested Version	Support from Version	Trigger Alarmscenario on VoIP start/stop	SIP in Archive	Notes
Brekeke PBX/SIP Server	2.1.6.6 2.4.3.0 2.4.9.0	5.2.8	x	x	Alarmscenarios can be triggered with SIP Brekeke SIP Plugin (see manual for further details). Brekeke PBX/SIP Server is part of SeeTec Enterprise Edition with Audio (SO200B0/1)
3CX Phone System	7.1	5.2.8	-	x	Alarmscenarios can be triggered if 3CX is able to send TCP Trigger on VoIP start/stop
Asterisk		5.2.8	-	x	Alarmscenarios can be triggered if Asterisk is able to send TCP Trigger on VoIP start/stop